

Infrared Motion Sensor

Type : Infrared Motion Sensor – Wide View (Recessed)

Model No : ES-P17C



Product Description :

Wide View Ceiling Mount Infrared Motion Sensor Light Switch

The product adopts good sensitivity detector, integrated circuit. It gathers automatism, convenient safe, saving-energy and practical functions. It utilizes the infrared energy from human as control-signal source, it can start the load at once when one enters detection field. It can identify day and night automatically. It is easy to install and used widely.

Specifications :

Part Number	:	B6114-1000MR
Detection Angle	:	360°
Power Source	:	AC 220-240V
Power Frequency	:	50 Hz
Rated Load	:	Max. 1000W LED
Detection Distance	:	2-20 Meters
Time Delay	:	10 Sec-7 Min (Adjustable)
Ambient Light	:	<10-2000LUX (Adjustable)
Installation Height	:	2.2m – 4m
Working Temperature	:	-20°C~+40°C
Detection Motion Speed	:	0.6~1.5m/s
Working Humidity	:	<93%RH
Power Consumption	:	Approx 0.5W

▪ **Function :**

Can identify day and night: The consumer can adjust working state in different ambient light. It can work in the daytime and at night when it is adjusted on the “sun” position (max). It can work in the ambient light less than 3 LUX when it is adjusted on the “moon” position (min). As for the adjustment pattern, please refer to the testing pattern.

Time-Delay is added continually: When it receives the second induction signals within the first induction period, it will compute time once more on the basic of the first time-delay rest.